

---

## FC501 Addressable Fire Control Panels

The FC501 easy-to-programme control panel has a 4-line, 40 character per line, LCD module display with a backlight, which provides written information regarding the system status, such as temperature, CO level, and smoke level, and is also used for programming the control panel.

The front panel controls enable text and configuration changes.

The FC501 auto-addressing panel has 3 in 1 loops that can support up to 128 addressable devices and 32 zones.

There are two versions available (1.8A or 2.7A power supply), as well as an optional IP board.

**Figure 1: FC501 addressable fire control panel with FC500 repeater**



### Specifications

- The enclosure and front door are plastic.
- H x W x D: 369mm x 335mm x 115mm

# Features

## Additional Panel Features

- Up to 400mA current dynamically shared across 3 circuits in 1 loop
- Auto mapping with Intelli-Zone feature
- Online Help function
- USB interface dual role Host/Device
- Multi users and multi installers (Up to 2 installers, 8 users)
- Walk test function
- 4000 Event Log
- Loop break location
- On board PSTN communicator
- GSM/GPRS as external module
- Up to 4 repeaters and multifunction interfaces for printer / simplified fire brigade panels
- Event transmission through PSTN and IP
- Automatic drift compensation

## Software Features

- Fast and simple system configuration, also offline
- Transferable user database
- Device graphic displayed
- Battery and wiring calculation
- Customizable cables database
- Visualization of all the devices assigned to a single zone
- Remote real time visualization of control panel loop and zone status, and so on.
- Easy Remote user interface with control buttons (reset, silence, evacuate)
- Multilevel map based on a tree structure
- Access device data from any pages of the map
- Configuration downloadable to USB memory stick
- Capability to print zone label sheet for front panel customization

# Ordering information

**Table 1: Product and accessories ordering information**

<b>Order number</b>	<b>Product details</b>
<b>Variants</b>	
557.200.719	<b>FC501-L:</b> Triple Circuit Single Loop Panel Icons - 1,8A PSU
557.200.718	<b>FC501-H:</b> Triple Circuit Single Loop Panel English - 2,7A PSU
557.200.720	<b>FC501-HK:</b> Triple Circuit Single Loop Panel - 2,7A PSU, Icons
<b>Accessories: SKU Description</b>	
508.031.742	<b>FC500MFI:</b> Multifunctional Interface
508.031.743	<b>FC500IP3:</b> IP Module
508.032.036	<b>FC500BX:</b> Cabinet for Spare 38Ah Batteries
508.032.037	<b>USB 5m:</b> USB 5m cable type A
508.032.042	<b>FC500DISP</b> Spare Display
557.202.726	<b>FC-MAE:</b> FC500 Panels Monitoring Software
557.200.727	<b>FC500</b> FireClass Repeater


# Performance characteristics

**Table 2: Performance characteristics**

	FC501-L	FC501-H and FC501-HK	FC500
Dimensions H x W x D mm	369 x 335 x 115		234 x 345 x 55.7
Weight	3 kg		2.7kg
Operating Temp	-5°C ÷ 40°C		
Storage Temp	-40 ÷ 80 °C		
Humidity	Up to 95% Non Condensing		
Supply Voltage	230VaC 50Hz - 15/+10%		19 Vdc - 30 Vdc
PSU I <sub>max</sub>	1,8A	2,7A	130 mA (dc)
Aux output rated voltage	27,6 Vdc	27,6 Vdc	NA
Max Battery Size	12 Ah	12Ah - 38Ah external box	NA
Loop Power	200mA	400mA	NA
IP Rating	IP30		IP30
Enclosure colour (cabinet and door)	RAL 7035		

# Approvals

**Table 3: Approvals**

	 0051 19 Tyco Fire & Security GmbH, Victor von Bruns- Strasse 21, 8212 Neuhausen am Rheinfall, Switzerland.	CPR Approval			European Type Approvals						International Listings		
		EN 54-2	EN 54-4	EN 54-21	MED	LPCB	VDS	AFNOR	FNO	SB SC	FP ANZ	HK FSD	TFTF
FC501-L	DoP-2015-4218	x	x	x									
FC501-H FC501-HK	DoP-2015-4219	x	x	x									
FC500IP in FC501-L FC501-H FC501-HK	DoP-2015-4211			x									

All required Declarations and certificates are publically available on the website [www.fireclass.net](http://www.fireclass.net) and are searchable by number or model name. The above fire detection products are components designed for use in Addressable Systems exclusively available to registered partners only. They are intended for installation by trained registered personnel only. Systems should be installed and configured according to local regulations.

# Comparison of FC501, FC503, and FC506 features

**Table 4: Comparison of FC501, FC503, and FC506 features**

Feature	FC501	FC503	FC506
<b>Addressable loops</b>			
No. of Loops	1 Loop	1 Loop	2 Loops
Loop Splitter / Sub-Loops	3	3	6
Max Current Draw per Loop	0.5A*	1A*	1A*
No. of Devices	128	250	500
<b>Outputs</b>			
Fault	1	1	1
Fire	1	1	1
Programmable Open collector Outputs	2	2	2
USB Interface	1	1	1
RS232 Interface	1	1	1
RS485 Interface	1	1	1
24V (for RS485 Devices)	1 , Max Current: 0.5 A	1 , Max Current: 1 A	1 , Max Current: 1 A
24 V Auxiliary	1 , Max Current: 0.5 A	1 , Max Current: 1 A	1 , Max Current: 1 A
24V Resettable	1 , Max Current: 0.5 A	1 , Max Current: 1 A	1 , Max Current: 1 A
Sounder / NAC Outputs	2 , Max Current: 0.5 A per NAC	2 , Max Current: 0.5 A per NAC	2 , Max Current: 0.5 A per NAC
<b>Power supply</b>			
AC Mains Voltage	230Vac -15%/+10%, 50-60Hz		
PSUs	BAW75T24 (27.6V, 2.7A)	BAQ140T24 (27.6V, 5.5 A)	BAQ140T24 (27.6V, 5.5 A)
Maximum Battery Size (Inside Panel)	2 (12A/h)	2 (17A/h)	2 (17A/h)
Maximum Battery Capacity	38 Ah	38 Ah	38 Ah
Battery Optional Box	YES	YES	YES
Panel Cabinet	Plastic Box	Metal Box, Plastic Door	Metal Box, Plastic Door
<b>Management software</b>			
Software	FireClass console	FireClass console	FireClass console

**Table 4: Comparison of FC501, FC503, and FC506 features**

Feature	FC501	FC503	FC506
Communication Channels	RS232, USB, RS485,IP	RS232, USB, RS485,IP	RS232, USB, RS485,IP
SW Zones	32	128	256
Number of zonal LEDs	8	8	8
Auto Addressing	YES	YES	YES
Events logged	4000	4000	4000
FC500 MFI Interface	4	4	4
FC500 Repeaters	4	8	8
FC500 Clients	No Support	7	7
<b>Standard compliance</b>			
EN54-2	x	x	x
EN54-4	x	x	x
EN54-21	x	x	x
<b>Communicators</b>			
PSTN (Voice, Data)	On Board	On Board	On Board
IP	FC500IP (Add On)	FC500IP (Add On)	FC500IP (Add On)

- ① **Note:** \*Absolute maximum value, the panel displays a warning on the screen when the current exceeds 80% of the maximum value.

