

## DS-PM1-O1H-WE Wall Switch



DS-PM1-O1H-WE Wall Switch is a device to control electrical power supply remotely. The device can directly connect to 100~240VAC source and open/close circuit manually via APP/Keypad/Keyfob or automatically by linking to different system events.

- 868 MHz two-way wireless communication
- AES-128 encryption
- LED display, show status of device and replay on/off display
- Small case design, which can be put into hiding places easily
- Automation operating, one button turn on/off from APP/Keypad/Keyfob
- Setting scenarios by different events



## ▪ Specification

Software features	
Scenario setting	By Alarm, By Operation, By Fault, By Schedule, By Manual
Learning button	1, For register
Hardware features	
Serial port	1, for debug
Electrical characteristics	
Power supply	AC 100 V to 240 V, 50/60 HZ
Operation humidity	10% to 90%
Operation temperature	-10 °C to 55 °C
Wireless transmission	
RF frequency	868 MHz
RF method	Two way communication
RF modulation	2GFSK
RF distance	1600 m
Wireless security	AES-128
Display	
LEDs status	3, Register/Signal (Green/Red), Power (Green), Relay Status (Blue)
General	
Installation method	Wall Mounting or Inside 86 box
Dimension(W x H x D)	38 x 25 x 18 mm
Shell material	Plastic
Color	White
Weight	31.5 g
Device management	
Relay output	1, NO/NC (AC 100~240 V, Max 13 A)

## ▪ Available Model

DS-PM1-O1H-WE

Distributed by

**HIKVISION®****Headquarters**

No.555 Qianmo Road, Binjiang District,  
Hangzhou 310051, China  
T +86-571-8807-5998  
overseasbusiness@hikvision.com

**Hikvision USA**  
T +1-909-895-0400  
sales.usa@hikvision.com

**Hikvision Australia**  
T +61-2-8599-4233  
salesau@hikvision.com

**Hikvision India**  
T +91-22-28469900  
sales@pramahikvision.com

**Hikvision Canada**  
T +1-866-200-6690  
sales.canada@hikvision.com

**Hikvision Thailand**  
T +662-275-9949  
sales.thailand@hikvision.com

**Hikvision Europe**  
T +31-23-5542770  
sales.eu@hikvision.com

**Hikvision Italy**  
T +39-0438-6902  
Info.it@hikvision.com

**Hikvision Brazil**  
T +55 11 3318-0050  
Latam.support@hikvision.com

**Hikvision Turkey**  
T +90 (216)521 7070- 7074  
sales.tr@hikvision.com

**Hikvision Malaysia**  
T +601-7852-2413  
sales.my@hikvision.com

**Hikvision UK & Ireland**  
T +01628-902140  
sales.uk@hikvision.com

**Hikvision South Africa**  
Tel: +27 (10) 0351172  
sale.africa@hikvision.com

**Hikvision France**  
T +33(0)1-85-330-450  
info.fr@hikvision.com

**Hikvision Kazakhstan**  
T +7-727-9730667  
nikia.panfilov@hikvision.ru

**Hikvision Vietnam**  
T +84-974270888  
sales.vt@hikvision.com

**Hikvision UAE**  
T +971-4-4432090  
salesme@hikvision.com

**Hikvision Singapore**  
T +65-6684-4718  
sg@hikvision.com

**Hikvision Spain**  
T +34-91-737-16-55  
info.es@hikvision.com

**Hikvision Tashkent**  
T +99-97-1238-9438  
uzb@hikvision.ru

**Hikvision Hong Kong**  
T +852-2151-1761  
info.hk@hikvision.com

**Hikvision Russia**  
T +7-495-669-67-99  
saleru@hikvision.com

**Hikvision Korea**  
T +82-(0)31-731-8817  
sales.korea@hikvision.com

**Hikvision Poland**  
T +48-22-460-01-50  
info.pl@hikvision.com

**Hikvision Indonesia**  
T +62-21-2933759  
Sales.Indonesia@hikvision.com

**Hikvision Colombia**  
sales.colombia@hikvision.com